



# LINZ E1S10M I KE Three-phase alternator 230V/400V 7 kVA 50 Hz AVR + Compound

## Product description:

**E1S-KE** series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency

  

- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND AND AVR
- Application: PORTABLE

Prodotto disponibile in versione 50 Hz e 60 Hz

## Product features:

Phase: Three phase

Continuous power three phase (KW): 5.6

Continuous power three phase (KVA): 7

Frequency (Hz): 50 / 60



Voltage (V): 230 / 400  
Engine rpm (rpm): 3000  
Alternator: Synchronous  
Poles: 2  
Single-phase power (KVA): 7  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 294  
Width (mm): 195  
Height (mm): 295  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: AVR+Compound  
Weight (Kg): 37

