



# LINZ E1S10M 1 KE Three-phase alternator 277V/480V 8.5 kVA 60 Hz AVR + Compound

## Product description:

**E1S-KE** series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

## CHARACTERISTICS

- Possibility to feed any type of load
  - Compact and easy to assemble
  - High starting capacity
  - High efficiency
- 
- Type: Three-phase alternators
  - Poles: 2
  - Phases: Three-phase
  - Regulation: COMPOUND AND AVR
  - Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 6.8

Continuous power three phase (KVA): 8.5

Frequency (Hz): 60

Voltage (V): 277 / 480



---

Engine rpm (rpm): 3600  
Alternator: Synchronous  
Poles: 2  
Single-phase power (KVA): 8.5  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 294  
Width (mm): 195  
Height (mm): 295  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: AVR+Compound  
Weight (Kg): 37

