



# LINZ E1S10L L KE Three-phase alternator 277V/480V 11 kVA 60 Hz AVR + Compound

## Product description:

**E1S-KE** series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND AND AVR
- Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 8.8

Continuous power three phase (KVA): 11

Frequency (Hz): 60

Voltage (V): 277 / 480

---



---

Engine rpm (rpm): 3600  
Alternator: Synchronous  
Poles: 2  
Single-phase power (KVA): 11  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 294  
Width (mm): 195  
Height (mm): 295  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: AVR+Compound  
Weight (Kg): 41.4