



CAT CATERPILLAR P INV2000 INVERTER SILENT GENERATOR

Product description:

PORTABLE GENERATOR

- Equipped with dual USB input
- Extremely quiet and fuel efficient
- Has two access doors to make it easier to change oil, air filter or drain fuel
- Works with LED lighting for night use

Main features of CAT P INV2000:

- Single switch for operation
- Dual USB input for charging phones, laptops, tablets
- Sockets protected from the elements, dust, humidity, dirt in general, thanks to the rubber covers with snap fastening
- Control panel with LED lighting for night operation
- Intelligent engine control (ESC) saves fuel while generating energy
- Air filter access and fuel drainage door

The images are purely indicative.

Product features:

Phase: Single phase

Maximum power single phase (KW): 2

Continuous power single phase (KW): 1.8

Maximum power single phase (KVA): 2.5

Continuous power single phase (KVA): 2.25





Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 13A, 1 x 5V 2.1A USB, 1 x 5V 1.0A USB, 1 x 12V DC 8.3A

Engine: OHV

Engine rpm (rpm): Variable

Starting system: Pull starter

Engine capacity (cm³): 79.5

Fuel tank capacity (L): 4

Consumption (L/h): 0.68 at 50% of the load

Running time (h): 4 to 50% of load

Width (mm): 318

Height (mm): 460

Dry weight (Kg): 22.1

Silenced: Yes

ATS Switch device : No

Voltage regulator: Inverter

Engine manufacturer: Caterpillar