



# LINZ PRO18S A/4 Three-phase alternator 4 poles 20 kVA 50 Hz AVR

## Product description:

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

## CHARACTERISTICS

- Compact and mechanically resistant
  - Excellent wave form
  - Minimum maintenance
  - High efficiency
- 
- Type: Three-phase alternators
  - Poles: 4
  - Phases: Three-phase
  - Regulation: AVR
  - Application: INDUSTRIAL, COGENERATION

## Product features:

Phase: Three phase

Continuous power three phase (KW): 16

Continuous power three phase (KVA): 20

Frequency (Hz): 50

Voltage (V): 230 / 400



Engine rpm (rpm): 1500  
Alternator: Synchronous  
Poles: 4  
Three-phase power (KVA): 20  
Protection degree: IP23  
Motor insulation class: H  
Length (mm): 460  
Width (mm): 362  
Height (mm): 373  
Brushes: No  
Type of alternator: Constant Speed  
Voltage regulator: AVR  
Weight (Kg): 121

