

## LINZ PRO18S A/4 Threephase alternator 4 poles 20 kVA 50 Hz AVR

## **Product description:**

Ø.

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

## **CHARACTERISTICS**

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, COGENERATION

## **Product features:**

Phase: Three phase Continuous power three phase (KW): 16 Continuous power three phase (KVA): 20 Frequency (Hz): 50 Voltage (V): 230 / 400

PrestaShop

Engine rpm (rpm): 1500 Alternator: Synchronous Poles: 4 Three-phase power (KVA): 20 Protection degree: IP23 Motor insulation class: H Length (mm): 460 Width (mm): 362 Height (mm): 373 Brushes: No Type of alternator: Constant Speed Voltage regulator: AVR Weight (Kg): 121

R

