



GENSET MH 6200 H/SA

Product price:

5,810.00 € tax excluded

Product description:

GENSET MH6200 H/SA 6,2KVA

GENSET MH6200 H/SA is a single-phase generator equipped with a Honda GX 390 OHV engine capable of delivering a maximum power of 6.2KVA.

The GENSET MH6200 H/SA is equipped with a practical electric start that allows a simple and fast use, in addition it is possible to request a remote control to control the generator from remote.

GENSET MH6200 H/SA is able to present specific solutions in the different fields of application of the generator set both for continuous use and for emergency use in case of interruption of the main grid.

All 6.2KVA GENSET MH6200 H/SA generators strictly comply with CE regulations regarding safety of use and control of polluting emissions. The picture is purely indicative.

This single-phase generator is super quiet, guaranteeing use in any environment, even in confined spaces where it is essential to keep noise pollution to a minimum.

The control panel supplied with the GENSET MH6200 H/SA provides the user with all the information related to the operation of the vehicular generator, control of oil level, operating temperature and current consumption with automatic shutdown of the engine in case of non-standard values.

TECHNICAL CHARACTERISTICS GENSET MH6200 H/SA

Phase Type: Single Phase

Maximum Single Phase Power: 6.2KVA

Fuel: Gasoline

Voltage: 230 V

Motor: Honda GX 390 OHV

Motor Rotation: 3000 rpm

Acoustic Power: 58 dB at 7 m

Power Factor: 0.8



Protection class: IP23

Isolation class: H

Fuel consumption 75% of load: 2.9 l/h

Fuel tank: 17 l

Length: 810 mm

Width: 505 mm

Height: 420 mm

Weight: 140 kg

Are you looking for a generator with different characteristics? [Here](#) you can find the full range of GENSET or other specialized brands.

Images and technical data are not binding and may be subject to revisions by the manufacturer.

Product features:

Phase: Single phase

Maximum power single phase (KVA): 6.2

Fuel: Gasoline

Voltage (V): 230

Engine: Yanmar L70N

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 390

Number cylinders: 1

Cooling: Air

Alternator: Synchronous

Consumption (L/h): 0.98 al 75% del carico

Acoustic power: 83 dB(A)

Acoustic pressure: 58 dB(A) at 7 m

Length (mm): 810

Width (mm): 778

Height (mm): 420

Dry weight (Kg): 140

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: No

Engine manufacturer: Yanmar

