



# GENMAC QUEEN-GAS G105GS GPL THREE- PHASE 105 KVA - Mecc Alte ALTERNATOR

## Product description:

### GENMAC QUEEN-GAS G105GS-GPL

The GENMAC QUEEN-GAS G105GS-GPL is a 105 KVA super-silenced single-phase/three-phase GPL generator set with Mecc Alte alternator and AVR voltage regulator.

Thanks to its natural gas fuel supply, the GENMAC QUEEN-GAS G105GS-GPL can only consume 44.3 Lt/h at full load and has a low environmental impact, making it one of the best in its class.

The long life and reliability of the GENMAC QUEEN-GAS G105GS-GPL is due to a special control procedure during the various stages of production.

The GENMAC QUEEN-GAS G105GS-GPL is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

Images and technical data are not binding.

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 92

Continuous power three phase (KW): 84

Maximum power three phase (KVA): 116

Continuous power three phase (KVA): 105

Fuel: LPG

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: Terminal box





Engine: General Motors RMG8800-D51-01

Engine rpm (rpm): 1500

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 8800

Number cylinders: 8

Oil capacity (L): 7.57

Cooling: Water

Alternator: Mecc Alte ECP34-2S/4A, self-excited

LPG consumption (L/h): 44.3

Width (mm): 1056

Height (mm): 1900

Dry weight (Kg): 1500

Silenced: Yes

Super silenced: Yes

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: General Motors

