



GENSET MG 132 S-I - SINGLE-PHASE/THREE-PHASE GENERATOR 132 KVA AVR

Product description:

GENSET MG 132 S-I

The GENSET MG 132 S-I is a 88 KVA single/three phase diesel generator set with electric start and AVR voltage regulator.

The GENSET MG 132 S-I also has a low fuel consumption: only 21.6 Lt/h at 75% of the load.

Thanks to the high quality and efficiency of its components, the GENSET MG 132 S-I generator set is ideal for various types of professional work such as on large construction sites.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 35.2

Maximum power single phase (KVA): 44

Maximum power three phase (KW): 105.6

Continuous power three phase (KW): 96

Maximum power three phase (KVA): 132

Continuous power three phase (KVA): 120

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: Terminal box

Engine: FPT (IVECO) NEF45TM3 turbo

Emissions Regulations: Stationary Use

Engine rpm (rpm): 1500





Starting system: Electric
Engine capacity (cm³): 4500
Number cylinders: 4
Cooling: Water
Alternator: Synchronous
Protection degree: IP23
Motor insulation class: H
Fuel tank capacity (L): 230
Consumption (L/h): 21.6
Running time (h): 10.65
Acoustic power: 95 dB(A)
Acoustic pressure: 70 dB(A) at 7 m
Length (mm): 2900
Width (mm): 1100
Height (mm): 1800
Dry weight (Kg): 1630
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : Yes
Voltage regulator: AVR
Engine manufacturer: FPT Iveco

