



NSM KR132 D - SINGLE PHASE ALTERNATOR 8.5 KVA AVR

Product description:

NSM KR132 D

The NSM KR132 D is a 8.5 KVA single-phase constant speed alternator with AVR voltage regulator.

This alternator belongs to the industrial category with 4 poles of 1500 rpm.

The versatility of NSM products and their robust design make the industrial series suitable to meet the requirements of industry and the most demanding technological specifications required in various applications.

The digital AVR gives the user the peace of mind of having a reliable, high-performance product with protection for all types of loads and greater voltage accuracy in electrical equipment.

To couple the NSM KR132 D alternator to a main engine, you can choose between these flanges and discs:

- SAE 4 disc joint 6.5
- SAE 4 disc joint 7.5
- SAE 5 disc joint 6.5
- SAE 5 disc joint 7.5

Please check the compatibility of the available couplings with your engine before placing your order.

Not binding images and technical data.

Product features:

Phase: Single phase





Maximum power single phase (KW): 8.5
Maximum power single phase (KVA): 8.5
Frequency (Hz): 50
Voltage (V): 230
Engine rpm (rpm): 1500
Poles: 4
Single-phase power (KW): 8.5
Single-phase power (KVA): 8.5
Efficiency (%): 79
Protection degree: IP20
Motor insulation class: H
Brushes: Yes
PMG: No
Product type: Alternator
Type of alternator: Constant Speed
Voltage regulator: AVR
Weight (Kg): 60