

NSM C132 XSB - SINGLE PHASE ALTERNATOR 6.5 KVA CAPACITOR

Product description:

NSM C132 XSB

Ì

The NSM C132 XSB is a 6.5 KVA single-phase constant speed alternator with capacitor voltage regulator.

This alternator belongs to the industrial category with 4 poles of 1500 rpm.

The versatility of NSM products and their robust design make the industrial series suitable to meet the requirements of industry and the most demanding technological specifications required in various applications.

To couple the NSM C132 XSB alternator to a main engine, you can choose between these flanges and discs:

- J609b (cone 25.4 35)
- B3/B9 cone 30
- B34
- SAE 3 disc joint 8
- SAE 3 disc joint 10
- SAE 3 disc joint 11.5
- SAE 4 disc joint 6.5
- SAE 4 disc joint 7.5
- SAE 4 disc joint 8
- SAE 4 disc joint 10
- SAE 5 disc joint 6.5
- SAE 5 disc joint 7.5
- SAE 5 disc joint 8

Please check the compatibility of the available couplings with your engine before placing your order.

R)

Not binding images and technical data.

Product features:

R

Phase: Single phase Maximum power single phase (KW): 6.5 Maximum power single phase (KVA): 6.5 Frequency (Hz): 50 Voltage (V): 230 Engine rpm (rpm): 1500 Poles: 4 Single-phase power (KW): 6.5 Single-phase power (KVA): 6.5 Efficiency (%): 80 Protection degree: IP23 Motor insulation class: H Brushes: No PMG: No Product type: Alternator Type of alternator: Constant Speed Voltage regulator: Capacitor Weight (Kg): 60