

NSM Z132 XSB - SINGLE PHASE/THREE PHASE ALTERNATOR 10 KVA COMPOUND

Product description:

NSM Z132 XSB

The NSM Z132 XSB is a 10 KVA single-phase/three-phase constant speed alternator with Compound voltage regulator.
This alternator belongs to the industrial category with 4 poles of 1500 rpm.
The versatility of NSM products and their robust design make the industrial series suitable to meet the requirements of industry and the most demanding technological specifications required in various applications.

To couple the NSM Z132 XSB alternator to a main engine, you can choose between these flanges and discs:
- J609b (cone 25.4 - 35)
- B3/B9 cone 30
- B34
- SAE 3 disc joint 8
- SAE 3 disc joint 10
- SAE 3 disc joint 11.5
- SAE 4 disc joint 6.5
- SAE 4 disc joint 7.5
- SAE 4 disc joint 8
- SAE 4 disc joint 10
- SAE 5 disc joint 6.5
- SAE 5 disc joint 7.5
- SAE 5 disc joint 8

Please check the compatibility of the available couplings with your engine before placing your order.

Not binding images and technical data.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 4
Maximum power single phase (KVA): 4
Maximum power three phase (KW): 8
Maximum power three phase (KVA): 10
Frequency (Hz): 50
Voltage (V): 230 / 400
Engine rpm (rpm): 1500
Poles: 4
Single-phase power (KW): 4
Single-phase power (KVA): 4
Three-phase power (KW): 8
Three-phase power (KVA): 10
Efficiency (%): 81
Protection degree: IP23
Motor insulation class: H
Brushes: Yes
PMG: No
Product type: Alternator
Type of alternator: Constant Speed
Voltage regulator: Compound
Weight (Kg): 66