



NSM KR100 E - SINGLE PHASE ALTERNATOR 4.2 KVA AVR

Product description:

NSM KR100 E

The NSM KR100 E is a 4.2 KVA single-phase constant speed alternator with AVR voltage regulator.

This alternator belongs to the portable category with 2 poles of 3000 rpm.

The versatility of NSM products and their robust design make the industrial series suitable to meet the requirements of industry and the most demanding technological specifications required in various applications.

To couple the NSM KR100 E alternator to a main engine, you can choose between these flanges and discs:

- J609a cone 19
- J609b cone 22
- J609b cone 25.4
- B3/B9 cone 23

Please check the compatibility of the available couplings with your engine before placing your order.

Configuration included in the price: without top cover and without cable connector.

Not binding images and technical data.

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.2





Maximum power single phase (KVA): 4.2

Frequency (Hz): 50

Voltage (V): 230

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 4.2

Single-phase power (KVA): 4.2

Efficiency (%): 72

Protection degree: IP23

Motor insulation class: H

Brushes: Yes

PMG: No

Product type: Alternator

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 20

