



# CGM D11000 STAGE V

## **Product price:**

4.912,50 € tax excluded

## **Product description:**

CGM D11000 single-phase 11 KVA generator

CGM D11000 single-phase 11 KVA generator set with Kohler engine powered by STAGE V diesel at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM D11000 generator set consists of a Made in Italy alternator from Linz or NSM, self-excited without brushes and with **AVR** voltage regulator. The CGM D11000 generator set is equipped with electric start with 12V battery and with a low fuel consumption, in fact it consumes only 2,8 liters/hour at 75% of the load.

This CGM D11000 generator set is perfect for outdoor use such as for hobbyist use. Also available with a panel for automatic start with ATS.

The CGM D11000 is part of the CLASSIC DIESEL series and are characterized by lower consumption and a longer life expectancy than the gasoline powered range.

The CGM D11000 at 3000 rpm is suitable for emergency use only. It is not recommended for use for more than 6 hours continuously and for more than 500 hours per year.

#### **Technical characteristics of CGM D11000:**

Phase type: Single phase Maximum power: 10.9 KW Continuous power: 9.9 KW Maximum power: 12.1 KVA Continuous power: 11 KVA

Fuel: Diesel Voltage: 230 V Frequency: 50 Hz

Motor: KOHLER KD425





Engine speed: 3000 rpm

Starting: Electric

Voltage regulator system: AVR

Consumption: 2.8 Lt/h at 75% of the load

Tank capacity: 4 Lt

Autonomy: 1.4 h at 75% load

Length: 910 mm Width: 580 mm Height: 640 mm Weight: 170 Kg

Discover the full range reserved for generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

#### **Product features:**

Phase: Single phase

Maximum power single phase (KW): 10.9 Continuous power single phase (KW): 9.9 Maximum power single phase (KVA): 12.1 Continuous power single phase (KVA): 11

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 400

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE

Engine: Kohler KD 425

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000 Starting system: Electric Engine capacity (cm³): 851

Number cylinders: 2 Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 4 Consumption (L/h): 2.8 Running time (h): 1.4 Length (mm): 910 Width (mm): 580





Height (mm): 640 Dry weight (Kg): 170

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Kohler

