



CGM C16000TE

Product price:

3,360.00 € tax excluded

Product description:

CGM C16000TE three-phase generator 16KVA

CGM C16000TE Three-phase generator 16KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C16000TE generator is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with AVR voltage regulator.

The CGM C16000TE generator is equipped with electric start with 12V battery but also with manual recoil starter and with a low fuel consumption, in fact it consumes only 4,9 liters/hour at 75% of the load. This CGM C16000TE is perfect for outdoor use such as for hobby use.

The CGM C16000TE is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The CGM C16000TE at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM C16000TE generator:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 5.9 KVA / 4.7 KW

Continuous singlephase power: 5.3 KVA / 4.3 KW

Maximum threephase power: 17.6 KVA / 14.1 KW

Continuous threephase power: 16 KVA / 12.8 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: BRIGGS & STRATTON 23HP

Engine revolutions: 3000 rpm

Starting: Electric



Voltage regulator system: AVR

Consumption: 4.9 Lt / h at 75% of the load

Capacity tank: 15 Lt

Autonomy: 3.1 h at 75% of the load

Length: 910 mm

Width: 580 mm

Height: 640 mm

Weight: 125 Kg

Discover the full range reserved for [generator](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 4.7

Continuous power single phase (KW): 4.3

Maximum power single phase (KVA): 5.9

Continuous power single phase (KVA): 5.3

Maximum power three phase (KW): 6.2

Continuous power three phase (KW): 12.8

Maximum power three phase (KVA): 17.6

Continuous power three phase (KVA): 16

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration:

Engine: Briggs&Stratton

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Elettrico

Engine capacity (cm³): 627

Number cylinders: 2

Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 15

Consumption (L/h): 4.9



Running time (h): 3.1

Length (mm): 910

Width (mm): 580

Height (mm): 640

Dry weight (Kg):

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

