



## SINCRO SK160 MB SINGLE-THREE-PHASE ALTERNATOR 20KVA AVR

## **Product description:**

Three phase brushless alternator - AVR.

- Insulation class H
- IP23
- Standard voltage 230/400 V 50 Hz
- Three phase leads 12 / single phase leads 4
- Bearings: Bearings are dimensioned for heavy duty
- Transient features: Transient voltage drop for rated step load at 0.8 power factor is less than 18%
- Single-phase operation: IB4 alternators can be connected for single-phase use
- Tropicalizzation: standard

The image is purely indicative.

## **Product features:**

Phase: Single phase / Three phase

Frequency (Hz): 50 Voltage (V): 400

Engine rpm (rpm): 1500

Poles: 4

Single-phase power (KW): 9.6 Single-phase power (KVA): 12 Three-phase power (KW): 16 Three-phase power (KVA): 20

Efficiency (%): 86





Protection degree: IP23 Dry weight (Kg): 99 Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

