



# MOSA GE SX-18000 KDT

#### **Product price:**

6,428.00 € tax excluded

### **Product description:**

## **MOSA GE SX-18000 KDT 14,4 KW**

MOSA GE SX-18000 KDT threephase 14,4 KW generator set with Kohler diesel engine. The MOSA GE SX-18000 KDT generator set is equipped with electric start. The alternator of the MOSA GE SX-18000 KDT generator set is synchronous, threephase, self-excited, self-regulated with class H insulation.

This MOSA is compact and convenient to maneuver and transport thanks to its compact size, its weight of 370 kg as well as the practical central hook for lifting.

The MOSA GE SX-18000 KDT generator set with 38-liter fuel tank has a fuel consumption of 3,7 liters/hour at 75% load for an autonomy of more than 10 hours.

### selecting Automatic version:

- PAC28 (40A) Remote control panel (only for AUTOMATIC models) optional accessory. Sockets:

1x 400V 32A 3P+N+E CEE

1x 230V 32A 2P+E CEE

1x 230V 16A 2P+E CEE

#### selecting STANDARD version:

and prepared for PAC-I 28 (40A) 809ATS Remote control panel (optional accessory) Sockets:

1x 400V 16A CEE

2x 230V 16A CEE?

#### **Technical specifications MOSA GE SX-18000 KDT:**

Maximum power three-phase: 14.4 KW

Three-phase continuous use power: 13.2 KW

Maximum power three-phase: 18 KVA



Three phase continuous use power: 16.5 KVA Single-phase continuous use power: 9 KW Single-phase continuous use power: 9 KVA

Fuel: Diesel

Voltage: 230 V / 400 V Frequency: 50 Hz

Engine: Kohler KDW1003

Starting: Electric

Consumption: 3.7 Lt/h at 75% of the load

Length: 1784 mm Width: 710 mm Height: 1115 mm Weight: 370 Kg Supersilenced

MOSA GE SX-18000 KDT portable generator set - Kohler diesel engine electric start - Threephase alternator

If you are looking for another product such as MOSA GE SX-18000 KDT generator set then you can browse our catalog for more <u>terrestrial generator sets</u>.

Images and technical data are not binding.

#### **Product features:**

Phase: Single phase / Three phase
Continuous power single phase (KW): 9
Continuous power single phase (KVA): 9
Maximum power three phase (KW): 14.4
Continuous power three phase (KW): 13.2
Maximum power three phase (KVA): 18
Continuous power three phase (KVA): 16.5

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230 / 400

Engine: KOHLER KDW1003 Emissions Regulations: Stage 5

Engine rpm (rpm): 3000 Speed governor: Mechanical Starting system: Elettrico Engine capacity (cm³): 1028

Number cylinders: 3 Oil capacity (L): 2.5



Cooling: Water

Alternator: Synchronous self-excited, self-regulated

Bore x stroke (mm): 75 x 77.6 Fuel tank capacity (L): 38 Consumption (L/h): 3..7 Running time (h): 10.5 Acoustic power: 93 dB(A)

Acoustic pressure: 68 dB(A) at 7 m

Length (mm): 1784 Width (mm): 710 Height (mm): 1115 Dry weight (Kg): 370

Silenced: Yes

Super silenced: Yes Product type: Generator ATS Switch device: No Voltage regulator: AVR

Engine manufacturer: Kohler

