



# CGM CS17000 SINGLE-PHASE GENERATOR STAGE V 17KVA

**Product price:**

**6,870.00 € tax excluded**

**Product description:**

## **CGM CS17000 SINGLE-PHASE GENERATOR STAGE V 17KVA**

CGM CS17000 single-phase generator of 17 KVA with BRIGGS & STRATTON engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use.

The CGM CS17000 generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The generator is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS17000 has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The CGM CS17000 is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 rpm, with BRIGGS & STRATTON diesel engine with electric start with key and battery.

### **Technical features of the CGM CS17000:**

Phase Type: Single-Phase

Maximum Power: 16,8 KW

Continuous Power: 15,3 KW

Maximum Power: 18,7KVA

Continuous Power: 17KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Engine: BRIGGS & STRATTON 31HP

Number of Cylinders: 2

Emission Standard: Stage V

Engine RPM: 3000 RPM

Boosting: Electric



Alternator: NSM made in Italy  
Voltage regulator system: AVR  
Consumption: 6. 5 Lt/h at 75% load  
Tank capacity: 60 Lt  
Autonomy: 9.2 h at 75% load  
Length: 1200 mm  
Width: 730 mm  
Height: 930 mm  
Weight: 290 Kg  
Supersilenced

Discover the full range of [current generator](#) from CGM on our catalog to find the one that best suits your needs.

Images and technical data not binding.

#### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 16.8  
Continuous power single phase (KW): 15.3  
Maximum power single phase (KVA): 18.7  
Continuous power single phase (KVA): 17  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 presa CEE 16A 3P 230V, n.1 presa CEE 32A 3P 230V, n. 1 presa CEE 63A 3P 230V  
Engine: BRIGGS & STRATTON 31HP  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Elettrico  
Engine capacity (cm<sup>3</sup>): 896  
Number cylinders: 2  
Alternator: NSM, made in Italy  
Fuel tank capacity (L): 60  
Consumption (L/h): 6.5 @ 75%



Running time (h): 9.2

Length (mm): 1200

Width (mm): 730

Height (mm): 930

Dry weight (Kg): 290

Silenced: Yes

Super silenced: Yes

Product type: Generator

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

