



# RENTAL POWER GENERATOR CS18000T SINGLE-PHASE / THREE- PHASE STAGE V

## Product description:

### RENTAL GENERATOR CS18000T SINGLE-PHASE / THREE-PHASE STAGE V 19,2KVA

Rental Power Generator CS18000T three-phase of 19,2 KVA with BRIGGS & STRATTON engine power by STAGE V Gasoline at 3000 rpm, compact and easy to use.

The Rental CS18000T generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The CGM CS18000T is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS18000T has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The Rental generator CS18000T is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This Rental generator is 3000 RPM, with BRIGGS & STRATTON engine with electric start with key and battery.

## The rental service

Generator rental has never been easier: choose the product you want to rent and [FILL OUT THE FORM](#).

Our specialized staff for the rental service will respond immediately with the most suitable offer for you!

The equipment available for rental can be shipped all over Italy and is always ready for action: our team of technicians ensures that it is always in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will use the rental service.



## Technical features of the CS18000T:

Phase Type: Single-phase / Three-phase

Singlephase Continuous Power: 5.8 KVA / 4.6 KW

Singlephase Maximum Power: 6.4 KVA / 5.1 KW

Threephase Continuous Power: 17.5 KVA / 14 KW

Threephase Maximum Power: 19.2 KVA / 15.3 KW

Power Factor cos fi?: 0. 8

VAC voltage: 230 / 400 V

Frequency (Hz): 50

Voltage regulator: AVR

Start framework: Manual / Automatic

Engine: BRIGGS & STRATTON 31HP

RPM: 3000

Power supply: Gasoline

Emissions standard: STAGE V

Fuel tank capacity: 60 l

Fuel consumption @ 75 % load: 6.5 l/h

Autonomy @ 75 % load: 9.2 h

Sound pressure: 72 dB(A) @ 7m

Length: 1200 mm

Width: 730 mm

Height: 930 mm

Net weight: 280 Kg

Manual electric panel with:

n. 1 CEE 16A 3P 230V socket

n. 1 CEE 32A 5P 400V socket

General switch

connector for ATS

hour counter

Discover the full range of [current generator](#) on [our catalog](#) to find the one that best suits your needs.

Pictures and technical data not binding.

## Product features:

Phase: Single phase / Three phase



Maximum power single phase (KW): 5.1  
Continuous power single phase (KW): 4.6  
Maximum power single phase (KVA): 6.4  
Continuous power single phase (KVA): 5.6  
Maximum power three phase (KW): 15.3  
Continuous power three phase (KW): 14  
Maximum power three phase (KVA): 19.2  
Continuous power three phase (KVA): 17.5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 230V 63A 3P CEE - 1 x 230V 16A 3P - 1 x 230V SCHUKO  
Engine: BRIGGS & STRATTON 31HP  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Manual / Automatic  
Engine capacity (cm<sup>3</sup>): 896  
Number cylinders: 2  
Cooling: Air  
Alternator: NSM, made in Italy  
Fuel tank capacity (L): 60  
Consumption (L/h): 6.5 @ 75 % del carico  
Running time (h): 9.2 @ 75 % del carico  
Length (mm): 1200  
Width (mm): 730  
Height (mm): 930  
Dry weight (Kg): 280  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Briggs&Stratton  
Video: MKDdx7hAnHc

