



LINZ PRO18S B/4 Threephase alternator 4 poles 30 kVA 60 Hz AVR

Product description:

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

CHARACTERISTICS

- Compact and mechanically resistant
- · Excellent wave form
- Minimum maintenance
- High efficiency

• Type: Three-phase alternators

• Poles: 4

Phases: Three-phaseRegulation: AVR

Application: INDUSTRIAL, COGENERATION

Product features:

Phase: Three phase

Continuous power three phase (KVA): 30

Frequency (Hz): 60 Voltage (V): 230 / 400 Engine rpm (rpm): 1800



Alternator: Synchronous

Poles: 4

Three-phase power (KVA): 25

Protection degree: IP23 Motor insulation class: H

Length (mm): 460 Width (mm): 362 Height (mm): 373

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR Weight (Kg): 134.5

