



# LINZ PRO18S C/4 Three-phase alternator 4 poles 36 kVA 60 Hz AVR

## Product description:

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

## CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, COGENERATION

## Product features:

Phase: Three phase

Continuous power three phase (KW): 24

Continuous power three phase (KVA): 36

Frequency (Hz): 60

Voltage (V): 230 / 400





Engine rpm (rpm): 1800  
Alternator: Synchronous  
Poles: 4  
Three-phase power (KVA): 30  
Protection degree: IP23  
Motor insulation class: H  
Length (mm): 460  
Width (mm): 362  
Height (mm): 528  
Brushes: No  
PMG: No  
Type of alternator: Constant Speed  
Voltage regulator: AVR  
Weight (Kg): 150

