



# MASE MARINER 2806 KS SINGLE PHASE MARINE GENERATOR SILENCED 30KW EPA

## Product description:

### **MASE MARINER 2806 KS SILENCED SINGLE-PHASE MARINE GENERATOR 30 KW EPA**

MASE MARINER2806KS single-phase silenced marine generator is equipped with a KUBOTA V3300 Diesel engine with **EPA emissions standard**, capable of delivering a maximum power of 30 KW at 1800 rpm.

The MASE MARINER2806KS alternator is a 4-pole synchronous, self-regulated, self-excited, brushless alternator, which in combination with the powerful KUBOTA engine can deliver a maximum power of 30 KW. The alternator is complete with AVR voltage regulator that ensures the stability of the voltage delivered by the generator, delivering current like the one at home.

The MASE MARINER2806KS allows easy access for maintenance of the alimentation and lubrication systems, seawater pump, air filter, oil filter and fuel. It is also equipped with safety systems of auto stop for low oil pressure and high temperature engine or exhaust gas.

The MASE MARINER2806KS is equipped with a soundproof cabin that makes it super silent, with a sound emission of 56dB(A) at a distance of 7 m. The painted aluminum soundproofing cabin is extremely lightweight and of very high resistance to external agents.

The MASE MARINER2806KS marine generator has **EPA certification** valid only **for the US market**.

## TECHNICAL FEATURES MASE MARINER2806KS

Phase Type: Single Phase

Maximum Power: 30 KW

Fuel: Diesel



---

Voltage: 120 - 240 V  
Frequency: 60 Hz  
Engine: KUBOTA V3300, 4 Stroke  
Emissions Standard: EPA  
Mechanical Power: 47. 3 Hp  
Number of cylinders: 4  
Displacement: 3318 cc  
Engine RPM: 1800 rpm  
Fuel consumption: 13 l/h  
Sound pressure: 56 dB(A) @ 7 m  
Alternator: Synchronous Brushless  
Voltage regulator: AVR  
Length: 1310mm  
Width: 640 mm  
Height: 830 mm  
Weight: 630 Kg

If you are looking for another marine generator then you can browse the entire catalog of [marine generators](#).

Images and technical data are not binding.

#### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 30  
Fuel: Diesel  
Frequency (Hz): 60  
Voltage (V): 120 / 240  
Engine: KUBOTA V3300  
Emissions Regulations: EPA  
Engine rpm (rpm): 1800

---



Speed governor: Electronic  
Engine capacity (cm<sup>3</sup>): 3318  
Number cylinders: 4  
Cooling: Air  
Inyección : Indirect  
Alternator: Synchronous, self-excited  
Poles: 4  
Lubrication: Forced  
Consumption (L/h): 13 at 100% of the load  
Acoustic pressure: 56 dB(A) at 7 m  
Length (mm): 1310  
Width (mm): 640  
Height (mm): 830  
Dry weight (Kg): 630  
Inverter: No  
AVR: Yes  
Compound: No  
Silenced: Yes  
Super silenced: Yes  
Voltage regulator: AVR

