



# GENERATOR SINGLE-PHASE / THREE-PHASE STAGEV 19,2KVA AVR

**Product price:** 

6,810.00 € tax excluded

## **Product description:**

## **GENERATOR SINGLE-PHASE / THREE-PHASE STAGEV 19,2KVA AVR**

Generator single-phase / three-phase of 19,2 KVA with BRIGGS & STRATTON engine powered by STAGEV Gasoline at 3000 rpm, compact and easy to use.

The generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The generator is equipped with electric start with battery that allows a practical and fast use even when cold. The generator has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The generator is not supplied with feet as these are supplied separately.

The generator is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 RPM, with BRIGGS & STRATTON engine with electric start with key and battery.

### STAGEV EMISSIONS REGULATION

The generator is equipped with a "mobile" STAGEV motorization, as required by the European Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate matter and nitrogen oxides delivered by the generator into the environment, and ensure a reduction in the environmental impact of 200% compared to standard engines.

#### **TECHNICAL FEATURES**

Phase Type: Single-phase / Three-phase

Singlephase Continuous Power: 5.8 KVA / 4.6 KW Singlephase Maximum Power: 6.4 KVA / 5.1 KW Threephase Continuous Power: 17.5 KVA / 14 KW



Threephase Maximum Power: 19.2 KVA / 15.3 KW

Power Factor cos fi?: 0. 8 VAC voltage: 230 / 400 V

Frequency (Hz): 50 Voltage regulator: AVR

Start framework: Manual / Automatic Engine: BRIGGS & STRATTON 31HP

RPM: 3000

Power supply: Gasoline

Emissions standard: STAGE V

Fuel tank capacity: 60 l

Fuel consumption @ 75 % load: 6.5 l/h

Autonomy @ 75 % load: 9.2 h Sound pressure: 72 dB(A) @ 7m

Length: 1200 mm Width: 730 mm Height: 930 mm Net weight: 280 Kg

Manual electric panel with: n. 1 CEE 16A 3P 230V socket n. 1 CEE 32A 5P 400V socket General switch connector for ATS

hour counter

Discover the full range of <u>current generator</u> on <u>our catalog</u> to find the one that best suits your needs.

Pictures and technical data not binding.

#### **Product features:**

Phase: Single phase / Three phase
Maximum power single phase (KW): 5.1
Continuous power single phase (KW): 4.6
Maximum power single phase (KVA): 6.4
Continuous power single phase (KVA): 5.6
Maximum power three phase (KW): 15.3
Continuous power three phase (KW): 14
Maximum power three phase (KVA): 19.2



Continuous power three phase (KVA): 17.5

Fuel: Gasoline Frequency (Hz): 50 Voltage (V): 230 / 400

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 400V 32A 5P

Engine: BRIGGS & STRATTON 31HP

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Manual / Automatic

Engine capacity (cm³): 896

Number cylinders: 2

Cooling: Air

Alternator: NSM, made in Italy Fuel tank capacity (L): 60

Consumption (L/h): 6.5 @ 75 % del carico Running time (h): 9.2 @ 75 % del carico

Length (mm): 1200 Width (mm): 730 Height (mm): 930 Dry weight (Kg): 280

Silenced: Yes

Super silenced: Yes Product type: Generator ATS Switch device: Optional

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

Video: MKDdx7hAnHc

