



MOSA GE 3600 BMI GENERATOR 4 KW SUPER SILENT INVERTER STAGEV

Product description:

MOSA GE3600BMI GENERATOR 4 KW SUPERSILENCED INVERTER STAGEV

MOSA GE3600BMI is a supersilenced single-phase generator, equipped with a GENKINS OHV 225 StageV petrol-powered engine, delivering a maximum power of 4KW, complete with **inverter voltage regulator**.

Even quieter and more efficient than traditional models, the MOSA GE3600BMI inverter genset delivers up to 4KW in single-phase mode, suitable for powering sophisticated electronic equipment that is sensitive to voltage and frequency variations.

Thanks to inverter technology, it is therefore possible to quietly and easily enjoy all the little comforts of home wherever you are: lights, fans, a coffee machine, laptops, radio or TV.

The compact size and light weight make the supersilenced MOSA GE3600BMI extremely manageable and easy to transport thanks to the trolley with integrated wheels and pull-out telescopic handle, making it extremely versatile.

The 12 Lt tank allows a continuous operation of more 8 hours.

The safety of use is guaranteed by overload protection and engine shutdown for low oil level.

The super-silent MOSA GE3600BMI can also be used in parallel, i.e. it can be connected to another generator of the same type to deliver twice the power and increase efficiency.

The GE3600BMI is also equipped with two 230 V (16 A) domestic voltage sockets, two USB ports and a 12 V (5 A) battery charging socket to power lights, radios, TVs, small appliances, laptops and tablets, mobile phones and much more.

STAGEV EMISSIONS REGULATION

MOSA GE3600BMI equipped with "mobile" STAGEV motorization, as required by the European



Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate and nitrogen oxides delivered by the generator into the environment, and guarantee a reduction in environmental impact by 200% compared to standard engines.

Technical features MOSA GE3600BMI generator:

Phase type: Single phase

Continuous use power: 4 KVA / 4 KW

Maximum power 3.6 KVA / 3.6 KW

Motor: GENKINS 225 230M

Revs : Variable 3600 rpm

Emissions standard: StageV

Starting: Recoil with wrap-around car

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Socket panel: 2 x schuko 16A 230 V

Capacit tank: 12 l

Consumption at 75% load: 1.4 l / h

Autonomy: 8.5 h

Sound pressure: 66.8 dB (A) @ 7 m

Voltage regulator: Inverter

Length: 605 mm

Width: 432 mm

Height: 500 mm

Net weight: 42 Kg

Are you looking for a generator with different technical characteristics? [HERE](#) you can find the area dedicated to Mosa generators or other specialized brands.

The images and technical data are not binding and may be subject to revisions by the manufacturer.

Product features:

Phase: Single phase

Maximum power single phase (KW): 4

Continuous power single phase (KW): 3.6

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.6

Fuel: Gasoline



Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 2 x 230V 16A 2P+T SCHUKO
Engine: GK225
Emissions Regulations: Stage 5
Engine rpm (rpm): 3600
Starting system: Manual / Electric
Engine capacity (cm³): 223
Number cylinders: 1
Alternator: Permanent magnets, self-excited, brushless
Fuel tank capacity (L): 12
Consumption (L/h): 1.4
Running time (h): 8.5
Acoustic power: 92 dB(A)
Acoustic pressure: 66 dB(A) at 7 m
Length (mm): 605
Width (mm): 432
Height (mm): 500
Dry weight (Kg): 42
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : No
Voltage regulator: Inverter

