



Shop name



USED CS18000T GENERATORE MONOFASE / TRIFASE STAGE V 19,2KVA

Product price:

4,000.00 € tax excluded

Product description:

USED GENERATOR CS18000T SINGLE-PHASE / THREE-PHASE STAGE V 19.2KVA

Used Generator CS18000T three-phase 19.2 KVA with BRIGGS & STRATTON engine powered by Petrol STAGE V at 3000 rpm, compact and easy to use.

The Used generator CS18000T is composed of a NSM Made in Italy alternator, self-excited without brushes and with voltage regulator **AVR**. The generator is equipped with electric starter with battery that allows for practical and fast use even when cold. The generator has low fuel consumption, in fact it consumes only 6.5 liters/hour at 75% of the load.

The Used CS18000T generator is part of the QUIET series because thanks to the canopy it has low noise emissions and is super-silenced. This generator is 3000 rpm, with a BRIGGS & petrol engine STRATTON electric start with key and battery.

Technical characteristics of the Used generator CS18000T:

Phase type: Single phase / Three phase

Continuous power single phase: 5.8 KVA / 4.6 KW

Maximum power single phase: 6.4 KVA / 5.1 KW

Continuous power three phase: 17.5 KVA / 14 KW

Maximum power three phase: 19.2 KVA / 15.3 KW

Power factor cos ϕ ?: 0.8

VAC voltage: 230 / 400 V

Frequency (Hz): 50

Voltage regulator: AVR

Starting panel: Manual / Automatic



Engine: BRIGGS & STRATTON 31HP
Revolutions per minute RPM: 3000
Power supply: Petrol
Emissions standard: STAGE V
Tank capacity: 60 l
Consumption @ 75 % of load: 6.5 l/h
Autonomy @ 75 % of load: 9.2 h
Sound pressure: 72 dB(A) @ 7m
Length: 1200 mm
Width: 730 mm
Height: 930 mm
Net weight: 280 Kg

Manual electrical panel with:
n.1 CEE socket 16A 3P 230V
n.1 CEE socket 32A 5P 400V
Main switch
connector for ATS
hour counter

Discover the entire range of [generator](#) on our catalog to find the one that best suits your needs.

Images and technical data are not binding. Please always consult the technical data sheet released by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 5.1
Continuous power single phase (KW): 4.6
Maximum power single phase (KVA): 6.4
Continuous power single phase (KVA): 5.6
Maximum power three phase (KW): 15.3
Continuous power three phase (KW): 14
Maximum power three phase (KVA): 19.2
Continuous power three phase (KVA): 17.5
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400



Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 400V 32A 5P

Engine: BRIGGS & STRATTON 31HP

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Manuale / Automatico

Engine capacity (cm³): 896

Number cylinders: 2

Cooling: Air

Alternator: NSM, made in Italy

Fuel tank capacity (L): 60

Consumption (L/h): 6.5 @ 75 % del carico

Running time (h): 9.2 @ 75 % del carico

Length (mm): 1200

Width (mm): 730

Height (mm): 930

Dry weight (Kg): 280

Silenced: Yes

Super silenced: Yes

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

Video: MKDdx7hAnHc

