



## PRAMAC GSW10Y COFANATO CON QUADRO COMANDO MANUALE (MCP)

## **Product description:**

## **Product features:**

Phase: Three phase

Maximum power three phase (KW): 465.34 Continuous power three phase (KW): 422.02 Maximum power three phase (KVA): 581.68 Continuous power three phase (KVA): 527.52

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 400

Engine: Doosan DP158LD, turbo intercooled

Speed governor: Electronic Starting system: Electric Engine capacity (cm³): 14618

Cooling: Water

Alternator: Mecc Alte ECO40-1L/4, brushless

Poles: 4

Fuel tank capacity (L): 636

Consumption (L/h): 87.2 at 75% of the load / 119.3 at 100% of the load

Running time (h): 7.3 at 75% of the load / 5.3 at 100% of the load

Length (mm): 3500 Width (mm): 1500 Height (mm): 2100 Dry weight (Kg): 3650

Silenced: No

Super silenced: No



ATS Switch device : Optional Voltage regulator: AVR Engine manufacturer: Doosan

