



AXO AIG 2002SM Single Phase Petrol Inverter Generator 2.2 kVA 1.76 kW

Product description:

The petrol Axo AIG 2002SM inverter unit is equipped with a multi-phase alternator+ inverter board with stabilised 220V single-phase output.

The THD (total harmonic distortion) value is less than 2%, the voltage accuracy is between +1% and -1%.

The overload capacity for starting is insignificant.

Connection

220 V: N.2 SCHUKO sockets 16A

12 V DC: N.2 screw type banana plugs one red (+) and one black (-)

Reading instrument

Multifunction digital instrument

Protections

10A fast fuse on the 12V DC

Recommended use

Sophisticated electronic equipment, computers, appliances that are microprocessor-controlled, electronic boards, electronic scales and likewise.

Safe use





Before use, check the electrical requirements of the user and the simultaneous start-up of the loads to connect to a compliant socket board.

The pictures are for illustrative purposes only.

Product features:

Phase: Single phase

Maximum power single phase (KW): 1.76

Continuous power single phase (KW): 1.6

Maximum power single phase (KVA): 2.2

Continuous power single phase (KVA): 2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 220V 16A SCHUKO

Engine: X4152F, OHV

Engine rpm (rpm): 4500

Starting system: Manual

Engine capacity (cm³): 125

Cooling: Air

Fuel tank capacity (L): 4.5

Consumption (L/h): 1.12~0.45

Running time (h): 4 - 10

Acoustic pressure: 59 dB(A) at 7 m

Length (mm): 545

Width (mm): 290

Height (mm): 500

Dry weight (Kg): 27

Silenced: Yes

Super silenced: No

ATS Switch device : No

Voltage regulator: Inverter

Engine manufacturer: Axo

