



PRAMAC P6000s SINGLE PHASE

Product price:

4,301.37 € tax excluded

Product description:

PRAMAC P6000s Single-phase 5.4 KW Super Silent Generator

The PRAMAC P6000s single-phase generator has a power output of 5.4 KW, powered by a diesel engine running at 3000 RPM. The PRAMAC P6000s generator is equipped with electric start. The alternator of the PRAMAC P6000s generator features a capacitor voltage regulator. The Yanmar diesel engine makes the P6000s generator very reliable as it is built and designed using high-quality materials.

Thanks to its casing, it can be considered super silent, and with its compact dimensions, it can be easily handled and transported. The PRAMAC P6000s single-phase generator is suitable for outdoor use in small construction sites or for small outdoor jobs.

Technical features of the PRAMAC P6000s Single-phase generator:

- Maximum Single-phase Power: 5.4 KW
- Continuous Single-phase Power: 4.4 KW
- Fuel: Diesel
- Voltage: 230 V
- Frequency: 50 Hz
- Engine: Yanmar L100N Electric
- Starting System: Electric
- Consumption: 1.94 Lt/h at 100% load
- Length: 970 mm
- Width: 580 mm
- Height: 927 mm
- Weight: 203 Kg

CONTROL PANEL



Controls:

- Start Key: OFF - ON - START
- Connector for automatic AMF/RSS panel

Instrumentation:

- Voltmeter

Protections:

- Circuit Breaker
- Differential Protection (DPP)
- Engine Protection Board: Low oil pressure; High engine temperature; Fuel reserve; Battery charge fault

Outlets:

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 16A IP44
- N.1 2P+T CEE 230V 32A IP44

The PRAMAC P6000s power generator is a professional diesel generator developed by Pramac with a diesel engine in a soundproofed and enclosed version, ideal for use in residential areas. The PRAMAC P6000s power generator, with its quiet operation, is the ideal generator for use in residential areas or outside working hours.

The P6000s generator is equipped with top-quality components, complete with protections and instrumentation.

If you are looking for a generator like the P6000s single-phase power generator, we recommend browsing our catalog of land-based generators to find the one that best suits your needs.

Images and technical data are non-binding.



Product features:

Phase: Single phase

Maximum power single phase (KW): 5.4

Continuous power single phase (KW): 4.4

Maximum power single phase (KVA): 5.9

Continuous power single phase (KVA): 4.9

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 2P+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Yanmar L100N Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm³): 435

Oil capacity (L): 1.6

Cooling: Air

Poles: 2

Fuel tank capacity (L): 19

Consumption (L/h): 1.45 at 75% of the load / 1.94 at 100% of the load

Running time (h): 13.10 at 75% of the load / 9.79 at 100% of the load

Acoustic power: 84 dB(A)

Acoustic pressure: 56 dB(A) at 7 m

Length (mm): 970

Width (mm): 580

Height (mm): 927

Dry weight (Kg): 203

Silenced: Yes

Super silenced: Yes

Product type: Generator

ATS Switch device : Optional

Voltage regulator: Capacitor

Engine manufacturer: Yanmar

