



# WFM SE12000-MTHE AVR

## Product description:

## Product features:

Phase: Single phase

Maximum power single phase (KW): 2.2

Maximum power single phase (KVA): 2.8

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A SCHUKO

Engine: Honda GX160

Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm<sup>3</sup>): 163

Number cylinders: 1

Oil capacity (L): 0.6

Cooling: Air

Fuel tank capacity (L): 3.6

Consumption (L/h): 1.5 at 100% of the load

Running time (h): 2.4 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 590

Width (mm): 390

Height (mm): 380

Dry weight (Kg): 36

Silenced: No



Super silenced: No  
ATS Switch device : No  
Voltage regulator: No  
Engine manufacturer: Honda