



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 2.7

Maximum power single phase (KVA): 3.4

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V

Engine: Honda GX200

Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 196

Number cylinders: 1

Oil capacity (L): 0.6

Cooling: Air

Fuel tank capacity (L): 3.6

Consumption (L/h): 1.6 at 100% of the load

Running time (h): 2.25 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 590

Width (mm): 390

Height (mm): 380

Dry weight (Kg): 40

Silenced: No

Super silenced: No

ATS Switch device : No



Shop name

Voltage regulator: No

Engine manufacturer: Honda



PrestaShop