



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase
Maximum power single phase (KW): 3.6
Maximum power single phase (KVA): 4.5
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 1 x 230V 16A - 1 x 230V 16A CEE
Engine: Honda GX270
Engine rpm (rpm): 3000
Ignition: Recoil
Starting system: Pull starter
Engine capacity (cm³): 270
Number cylinders: 1
Oil capacity (L): 1.1
Cooling: Air
Fuel tank capacity (L): 20
Consumption (L/h): 2.4 at 100% of the load
Running time (h): 8.33 at 100% of the load
Acoustic power: 95 dB(A)
Acoustic pressure: 70 dB(A) at 7 m
Length (mm): 750
Width (mm): 560
Height (mm): 620
Dry weight (Kg): 75
Silenced: No
Super silenced: No
ATS Switch device : No



Shop name

Voltage regulator: No

Engine manufacturer: Honda



PrestaShop