



WFM SE12000-MTHER AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 3.6

Maximum power single phase (KVA): 4.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A - 1 x 230V 16A CEE

Engine: Honda GX270

Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 270

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 2.4 at 100% of the load

Running time (h): 8.33 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 750

Width (mm): 560

Height (mm): 620

Dry weight (Kg): 75

Silenced: No



Super silenced: No
ATS Switch device : No
Voltage regulator: No
Engine manufacturer: Honda