



## WFM SE12000-MTHE AVR

## **Product price:**

1,446.00 € tax excluded

## **Product description:**

## **Product features:**

Phase: Single phase / Three phase Maximum power single phase (KW): 3 Maximum power single phase (KVA): 3.8 Maximum power three phase (KW): 6 Maximum power three phase (KVA): 7.5

Fuel: Gasoline Frequency (Hz): 50 Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V 16A 3P

**SCHUKO** 

Engine: Honda GX390 Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter Engine capacity (cm³): 389

Number cylinders: 1 Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 3.1 at 100% of the load Running time (h): 6.45 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 750 Width (mm): 560 Height (mm): 620 Dry weight (Kg): 86



Silenced: No

Super silenced: No ATS Switch device : No Voltage regulator: No

Engine manufacturer: Honda

