



WFM 7500-TSHE AVR

Product description:

GENERATORS WITH AVR

Generator sets with Honda petrol or Lombardini diesel engines, in open version on base or in soundproofed frame with power ratings from 4.5 to 12 KVA, single-phase or single-phase/three-phase, 3000 rpm, air-cooled with recoil starter or key starter, including battery and electrical panel with sockets and standard protection.

Indispensable for electronic users as they are all equipped with an output voltage stabiliser of less than 1%.

Compliance with Directive 2000/14/EC of 01/01/2006 concerning noise levels based on the model.

Recommended for domestic and professional users who connect highly sensitive electronic equipment:

- Inverter welders
- Power tools with circuit boards
- Electronics, accumulators
- Plasma TVs, computers
- Latest generation boilers
- Telephone switchboards
- Burglar alarms
- Uninterruptible power supplies
- HI-FI systems

Main features:

- Open or soundproof protective frame
- Original Honda or Lombardini engine
- Low oil level protection
- Silencer muffler
- Leading Italian brand alternator
- Recoil or electric start with 12V battery supplied with acid
- Full load test with test certificate
- User manual compliant with safety standards



The images are purely indicative.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 1.8

Maximum power single phase (KVA): 2.3

Maximum power three phase (KW): 5.6

Maximum power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 CEE 5P 400V 16A + 1 CEE 3P 230V 16A

Engine: Honda GX390, OHV

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 15

Consumption (L/h): 3.1 at 100% of the load

Running time (h): 4.83 at 100% of the load

Acoustic power: 88 dB(A)

Acoustic pressure: 63 dB(A) at 7 m

Length (mm): 1100

Width (mm): 540

Height (mm): 650

Dry weight (Kg): 140

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda

