



# MASE FX 12001 GH GENERATOR 11 KVA SINGLE PHASE STAGE V AVR

Product price:

**4.800,00 € tax excluded**

## Product description:

MASE FX 12001 GH GENERATOR 11 KVA SINGLE PHASE STAGE V AVR

MASE FX 12001 GH is a single-phase generator, equipped with a Gasoline engine Honda GX630 **StageV**, it delivers a maximum power of 11KVA, complete with AVR voltage regulator.

MASE FX 12001 GH is equipped with a user friendly electric starter, thanks to which the ignition of the group is incredibly easy and safe. MASE FX 12001 GH provides reliable power for home, business and leisure environments, safely powers home appliances and other electronic devices. Extremely practical sockets and controls make starting and operating the generator easier, making these operations extremely simple and fast.

## AVR VOLTAGE REGULATOR

The MASE FX 12001 GH generator is supplied complete with voltage regulator. The AVR is a device that allows you to **keep the output more constant and less dependent on the load**. Thanks to the AVR there are fewer drops or peaks in current and this makes the use of the various connected devices safer, improving their performance and duration.

## STAGEV EMISSIONS REGULATION

The generator is equipped with a "mobile" STAGEV motorization, as required by the European Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate matter and nitrogen oxides delivered by the generator into the environment, and ensure a reduction in the environmental impact of 200% compared to standard engines.

Technical characteristics of MASE FX 12001 GH



Phase type: Single phase  
Maximum power: 11 KVA / 8.8 KW  
Continuous use power: 10 KVA / 8 KW  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: Honda GX630  
Engine revs: 3000 rpm  
Emissions standard: Stage V  
Voltage regulator: AVR  
Starting: Electric  
Tank capacity: 29 l  
Consumption: 6 Lt / h at 75% of the load  
Acoustic pressure: 73 dB (A) @ 7 m  
Length: 940 mm  
Width : 488 mm  
Height: 823 mm  
Weight: 148 Kg

Are you looking for a product with different technical characteristics? [HERE](#) you can find the area dedicated to MASE generators or other specialized brands

Images and technical data are not binding and may be subject to revisions.

#### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 8.8  
Continuous power single phase (KW): 8  
Maximum power single phase (KVA): 11  
Continuous power single phase (KVA): 10  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 x 230V 16A 2P+T CE - 1 x 230V 32A 2P+T CE  
Engine: Honda GX630, 4 stroke, OHV  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 688  
Number cylinders: 2  
Cooling: Air  
Alternator: Synchronous



---

Fuel tank capacity (L): 29  
Consumption (L/h): 6 at 75% of the load  
Running time (h): 4.83 at 75% of the load  
Acoustic power: 98 dB(A)  
Acoustic pressure: 73 dB(A) at 7 m  
Length (mm): 940  
Width (mm): 488  
Height (mm): 823  
Dry weight (Kg): 148  
Silenced: No  
Super silenced: No  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Honda