



# TECNOGEN LD13000TE

## Product description:

Generating sets available in both single-phase and three-phase versions, with powers from 2.3 to 21 kVA MAX, equipped with gasoline or diesel engines, air-cooled, 3000 rpm, electric and/or manual starting with recoil starter. Compact, simplified and economical, they boast an excellent price/performance/size and weight ratio.

Easily transportable thanks to the reduced overall dimensions due to an essential equipment, they are suitable for all those who need an economic source of energy, however assembled with first-rate components that guarantee absolute reliability. The petrol versions of the COMPACT line, thanks to the latest generation Honda engines, fall within the parameters of the noise directive 2000/14/EC.

The image is purely indicative.

## Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3

Maximum power single phase (KVA): 3.8

Maximum power three phase (KW): 10.6

Maximum power three phase (KVA): 13.3

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine: HONDA GC160

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 954





Number cylinders: 2  
Cooling: Air  
Fuel tank capacity (L): 7  
Consumption (L/h): 3.3  
Running time (h): 2,5  
Length (mm): 920  
Width (mm): 520  
Height (mm): 660  
Dry weight (Kg): 190  
Silenced: No  
Super silenced: No  
ATS Switch device : Optional  
Voltage regulator: No  
Engine manufacturer: Lombardini