

GREEN POWER GP18S-PW-C - SOUNDPROOF



Product price:

7.859,00 € tax excluded

Product description:

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

There is a choice of versions:

- Super-silenced group with Compound-Linz alternator (automatic control unit)
- Super-silenced group with AVR-Leroy alternator (automatic control unit)
- Super-silenced group with AVR-Mecc High alternator (automatic control unit)
- Super-silenced group with AVR-Stamford alternator (automatic control unit)

The image is purely indicative.

Product features:

Phase: Three phase

Maximum power three phase (KW): 13.6

Continuous power three phase (KW): 12



Maximum power three phase (KVA): 17
Continuous power three phase (KVA): 15
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: Presa ausiliaria 32A 5P + Presa ausiliaria 32A 3P
Engine: PERKINS 403A-15G2
Emissions Regulations: NON EMISSIONATO
Engine rpm (rpm): 1500
Speed governor: Mechanical
Starting system: Elettrico
Engine capacity (cm³): 1496
Number cylinders: 3
Cylinders' position: In line
Cooling: Water
Alternator: Linz E1S13ME/4, synchronous, with brushes
Poles: 4
Fuel tank capacity (L): 70
Acoustic pressure: 70 dB(A) at 7 m
Length (mm): 1750
Width (mm): 700
Height (mm): 1125
Dry weight (Kg): 350
Silenced: Yes
Super silenced: Yes
ATS Switch device : Optional
Voltage regulator: Compound / AVR (optional)

