



# HONDA EU 30i Handy Petrol Inverter Generator 3 kW

## Product description:

Generator set HONDA EU30i Handy 3 KW super-silenced inverter

The generator set HONDA EU30i Handy is part of Honda's portable range and is a 3 KW single-phase, super-silenced, 3 KW generator with inverter technology voltage regulator.

The starting system of this generator is manual rope type with recoil starter.

This generator set is perfect for both hobby and professional use, thanks to the reliable Honda gasoline powered engine and all the high quality components of which it is composed.

The HONDA EU30i Handy is small but contains all the functions and innovations needed to ensure clean and environmentally friendly energy supply for the operation of sensitive electronic equipment in large outdoor environments.

The EU30i Handy generator set is one of the quietest in its category because it has been designed with soundproofed cladding and the exclusive silencer of the exhaust system.

The combination of lightweight materials such as magnesium, the folding handle and the stable, smooth wheels make the EU30i Handy portable genset extremely easy to carry.

The voltage regulator with inverter technology guarantees the HONDA EU30i Handy generator set a constant, clean and uninterrupted power supply with a quality comparable to home quality.

In this way, thanks to the exclusive inverter voltage regulator, you can connect your sensitive devices (PCs, smartphones, household appliances, etc.) to your EU30i Handy safely and without burning them.

The EU30i Handy generator set, like all Honda portable generators, is equipped with the exclusive load sensing device: the ECO-Throttle™. This device allows, as the load increases, to increase the revolutions of the generator automatically, so you will always have the energy you need without straining the generator. This also allows you to save a lot of fuel.

Another device present in all Honda portable generators is the Oil Alert™ technology that will automatically disconnect the contact in case the oil is below the safety level.



The EU30i Handy portable gensets can be connected to each other via a parallel cable that doubles the power. Connected in this way, they can meet the needs of small facilities such as power supply to ensure the operation of the air conditioner in a motorhome. Two smaller generators are easier to manage and transport than a large one and, once on site, can be connected to increase power.

When you purchase the EU30i Handy genset, you have the exclusive benefit of a national or commercial warranty, provided that the service program is adhered to.

If you need regular maintenance you can contact us by clicking on the link <https://www.manelservice.com/manutenzione>.

#### TECHNICAL DATA SHEET HONDA EU30i HANDY

Type: Single phase

Maximum output Single Phase (kW): 3

Rated output Single Phase (kW): 2.6

Maximum output Single Phase (kVA): 3.75

Rated output Single Phase (kVA): 3.25

Fuel : Petrol

Rated voltage (V): 230

Rated frequency (Hz): 50

Rated current (A): 3.9

Engine model: Honda GX160

Engine type: 4-stroke, OHV, 1 cylinder

Starter system: Recoil

Operating time at rated: 1.5

Length (mm): 622

Width (mm): 379

Height (mm): 489

Dry weight (kg): 35.2

Inverter

If you are looking for a portable super-silenced inverter generator set that gives you more power and has an electric key start, then we recommend the Honda EU30is.

Images and technical data are not binding.

#### Product features:

Phase: Single phase

Maximum power single phase (KW): 3

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA): 3.75





Continuous power single phase (KVA): 3.25

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 2P+T CEE

Engine: Honda GX160, 4 stroke, OHV

Engine rpm (rpm): 4000

Ignition: Transistorized

Starting system: Manual

Engine capacity (cm<sup>3</sup>): 163

Number cylinders: 1

Oil capacity (L): 0.53

Cooling: Air

Alternator: Multipolar

Bore x stroke (mm): 68 x 45

Fuel tank capacity (L): 5.9

Consumption (L/h): 1.54

Running time (h): 3.83

Acoustic power: 92 dB(A)

Acoustic pressure: 71 dB(A)

Length (mm): 622

Width (mm): 379

Height (mm): 489

Dry weight (Kg): 35.2

Silenced: Yes

Super silenced: Yes

Product type: Generator

ATS Switch device : No

Voltage regulator: Inverter

Engine manufacturer: Honda

Video: jTziyirxj-A

