

## STANLEY SG 5500



## **Product description:**

## **Product features:**

Phase: Single phase / Three phase Maximum power three phase (KW): 5.5 Continuous power three phase (KW): 3.6 Maximum power three phase (KVA): 6.88 Continuous power three phase (KVA): 4.5

Fuel: Gasoline Frequency (Hz): 50 Voltage (V): 230 / 400

Sockets configuration: 1 x 400V - 3 x 230V

Engine: CP188F, 4 stroke Engine rpm (rpm): 3000 Starting system: Electric Engine capacity (cm³): 389

Number cylinders: 1 Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous Fuel tank capacity (L): 25 Consumption (L/h): 2.73 Running time (h): 9.15

Acoustic power: 97 dB(A) a 4 m

Length (mm): 730 Width (mm): 590 Height (mm): 595 Dry weight (Kg): 91





Inverter: No AVR: Yes

Compound: No Silenced: No

Super silenced: No

