



Shop name



WFM 4200-SHE GAS WITH NATURAL GAS SUPPLY KIT INSTALLED

Product description:

WFM 4200-SHE GAS WITH METHANE POWER KIT

WFM 4200-SHE is a singlephase generator with an original HONDA petrol engine that can also be converted to LPG or methane gas, in a super sound-proof frame.

WFM 4200-SHE can deliver a maximum power of 4,5KVA single-phase, thanks to the powerful engine at 3000 rpm equipped with air cooling

The WFM 4200-SHE has a convenient key start and comes complete with battery and electrical panel with sockets and protection as standard.

The WFM 4200-SHE is a fully enclosed generator with large ventilation grills and comes standard with two small wheels for small movements, combined with the automatic intervention panel, they are the ideal solution for the home in case of blackout.

All WFM 4200-SHEs are compliant with Directive 2000/14/EC of 01/01/2006 regarding noise levels.

WFM 4200-SHE TECHNICAL FEATURES

Maximum SinglePhase Power: 3.6 KW
Maximum SinglePhase Power: 4.5 KVA
Fuel: LPG
Voltage: 230 V
Frequency: 50 Hz
Motor: Honda GX270
Start: Electric
Consumption: 2. 9 m³/h at 100% load
Length: 1000 mm
Width: 515 mm



Height: 595 mm

Weight: 106 Kg

- protection frame with high soundproofing
- original Honda engine complying with low CO2 emissions
- low oil level protection
- silencer muffler
- alternator of primary Italian brand
- electric start with 12V battery (supplied without acid)
- full load test with test certificate
- user manual complying with safety regulations
- can also be converted to LPG or methane gas

Are you looking for a generator with different technical characteristics? [Here](#) you can find the full range of WFM or other brands specializing in the field.

Images and technical data are indicative only and may be subject to revisions by the manufacturer.

Product features:

Phase: Single phase

Maximum power single phase (KW): 3.6

Maximum power single phase (KVA): 4.5

Fuel: Natural Gas

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE

Engine: Honda GX270, OHV

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 270

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Natural Gas consumption (m³/h): 2.9 at 100% of the load

Fuel tank capacity (L): 7

Acoustic power: 88 dB(A)

Acoustic pressure: 63 dB(A) at 7 m



Shop name

Length (mm): 1000

Width (mm): 515

Height (mm): 595

Dry weight (Kg): 106

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: No

Engine manufacturer: Honda



PrestaShop