



# SINCRO ER2 CBT Single Phase Synchronous AC Alternator 4.8 kVA Capacitor

## Product description:

### **SINCRO ER2 CBT ALTERNATOR 6,0KVA SINGLEPHASE**

Alternator SINCRO ER2 CBT singlephase with a power of 6,0KVA, this unit has a Brushless operation equipped with capacitor voltage regulator.

The alternator is foreseen to work at frequency 50 or 60 HZ, the possibility to work on these two frequencies makes possible its application for any service voltage increasing its versatility, for a correct operation.

All the components that make up the SINCRO ER2 CBT alternator are subjected to a specific coating and/or impregnation process aimed at safeguarding the functionality of the generator and protecting the critical peers in the various conditions of use.

For extreme atmospheric conditions, models are available that also guarantee the IP23 standard, which provides protection against water up to 60° from the vertical. SINCRO ER2 CBT is a brushless alternator, this feature together with the high efficiency of the regulator ensure a low level of interference with radio waves.

SINCRO alternators are all equipped with a voltage regulator, in the case of the SINCRO ER2 CBT with capacitor.

The purpose of the voltage regulator in a current generator is to keep the output stable. The lagging current opposes the inductor magnetic field, causing a voltage drop at the alternator output terminals; to compensate for this phenomenon, the regulator intervenes automatically by increasing the excitation current, until the output returns to the nominal value.

Basically, thanks to the regulator integrated in the SINCRO ER2 CBT you will have a greater safety avoiding malfunctions and sudden breakages of your working tools or daily use.



Select the alternator that reflects the **technical specifications you require**, visit our [dedicated section](#) to understand how.

## SINCRO ER2 CBT TECHNICAL FEATURES

Phase type: Single-phase

Maximum singlephase output: 4.8KW

Singlephase continuous output: 3.2KW

Maximum singlephase output: 6.0KVA

Singlephase continuous output: 4.8KVA

Frequency: 50-60Hz

Voltage: 230 V

Degree of protection: IP23

Alternator revolutions: 3000 rpm

Number of poles: 2

Weight: 21,3 Kg

Width: 212 mm

Length: 384 mm

Height: 203 mm

Without brushes

Voltage regulator: Capacitor

Alternator type: Constant speed

Looking for a product with different features? [Here](#) you can find the full range SINCRO and other specialized brands.

Images and technical data are not binding and subject to change by the manufacturer

### Product features:

Phase: Single phase

Frequency (Hz): 50

Voltage (V): 230

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 4.8

Single-phase power (KVA): 4.8

Efficiency (%): 78



Protection degree: IP23

Dry weight (Kg): 21.5

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: Capacitor

