



## SINCRO GK2 LB Single Phase Synchronous AC Alternator 25 kVA Capacitor

## **Product description:**

## SINCRO GK2 LB ALTERNATOR 31,0 KVA SINGLE-PHASE

Alternator SINCRO GK2 LB single-phase with a power of 31,0KVA, this unit has a Brushless operation equipped with capacitor voltage regulator.

The alternator is provided for operation at frequency 50 or 60 HZ, the possibility of working on these two frequencies makes it possible the application for any service voltage increasing its versatility, for the correct operation. SINCRO GK2 LB has been realized with the body entirely in steel, this makes the alternator very resistant and suitable for heavy duty use.

All the components that make up the SINCRO GK2 LB alternator are subjected to a specific coating and/or impregnation process in order to safeguard the generator's functionality and protect its critical peers under various conditions of use.

SINCRO GK2 LB is a brushless alternator, this feature together with the high efficiency of the regulator ensure a low level of interference with radio waves.

SINCRO alternators are all equipped with a voltage regulator, in the case of the GK2 LB capacitor model.

Select the alternator that meets the **technical specifications you require**, visit our <u>dedicated section</u> to find out how.

TECHNICAL FEATURES SINCRO GK2 LB

Phase Type: Single-phase

Maximum single-phase output: 24.8 KW

Maximum single-phase continuous output: 20.0 KW



Maximum single-phase output: 31.0 KVA

Maximum single-phase continuous output: 25.0 KVA

Frequency: 50-60 Hz

Voltage: 230 V

Protection class: IP23

Alternator speed: 3000 rpm

Number of poles: 2 Weight: 125 Kg

Brushless

Voltage regulator: Condenser Type of alternator: constant speed

Looking for a product with different characteristics? <u>Here</u> you can find the full range SINCRO and other specialized brands.

Images and technical data are not binding and subject to change by the manufacturer

## **Product features:**

Phase: Single phase Frequency (Hz): 50 Voltage (V): 230

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 25 Single-phase power (KVA): 25

Efficiency (%): 85

Protection degree: IP23

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: Capacitor

