



# SINCRO ET2 MCR Three Phase Synchronous AC Alternator 7 kVA AVR

## Product description:

Three phase brushes alternator - AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

## Product features:

Phase: Three phase  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Engine rpm (rpm): 3000  
Poles: 2  
Three-phase power (KW): 5.6  
Three-phase power (KVA): 7  
Efficiency (%): 78  
Protection degree: IP23  
Dry weight (Kg): 29.3  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: AVR

